



ENDRESS

Power Generators

ESE 2000I IP68

Order No. **110005.01**



Main features

Alternator type	synchron
Max. Output 1~ [kVA/kW]	2.0/2.0
Continuous Power 1~ [kVA/kW]	1.6/1.6
Nominal voltage [V]	230
Nominal Current [A]	8,7
Power factor cos (phi)	1
Frequency [Hz]	50
Protection Class [IP]	23

Engine

Engine Type	Yamaha MZ 80 / 3,5 HP
Design	1-cylinder 4-stroke OHV
Displacement [ccm]	79
Output 3000 rpm	1,8
CO2 emissions [g / kWh]	649,4
Fuel	Petrol
Fuel tank capacity [l]	4
Fuel consumption @ 75% PRP [L/h]	0,7
Running time @ 75% PRP	5,7
Starting system	Recoil starter
Sound power level LWA [db(A)]	89
Weight in kg ca.	21,3
Dimensions L x W x H [mm]	540 x 330 x 505
Shockproof sockets	1x 230 V / 16 A IP68 1x 12 V

This CO2 measurement results from testing over a fixed test cycle under laboratory conditions a(n) (parent) engine representative of the engine type (engine family) and shall not imply or express any guarantee of the performance of a particular engine'.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de



ESE 2000I IP68

Order No. 110005.01



Power Generators

Equipment features

According to the new DIN 14685-3

Protective contact socket IP68

Lack of oil automatic switch-off

Alternator overload protection

Variable speed constant frequency (VSCF)

Connection for a 12 V battery charge

выразить любую гарантию работы конкретного двигателя.

Power ratings according to ISO 8528-1: 2005

Technical data and illustrations are not binding. We assume no liability for misprints.

2020-2-19

ENDRESS Elektrogerätebau GmbH
Neckartenzlinger Str. 39
D - 72658 Bempflingen, Germany

Phone.: +49 (0) 7123-9737-0
Fax.: +49 (0) 7123-9737-50
www.endress-generators.de

